

Issued: 17 April 2019

Last update: 30 May 2019

- Black Hill relays date change to 14 August 2019. Addition of Easdale and Clachan frequency changes.

## Trade and Industry Information

### 700MHz Clearance Events

### STV Region

Following a decision by Ofcom, spectrum in the 700MHz UHF band currently used for digital terrestrial television (DTT) is being reallocated for the development of future mobile services. Some DTT multiplexes will be moving to new broadcast frequencies as a result of this change.

Engineering work for the 700MHz Clearance Programme will take place at transmitters across the UK between 2017 - 2020. Freeview viewers (and those with other services that use Freeview channels, such as YouView) will need to retune their TV equipment when changes take place in their area. This document lists the currently announced clearance events for the STV region and will be updated as new information is released. The latest version will always be available to download at [www.digitaluk.co.uk/clearance](http://www.digitaluk.co.uk/clearance). Details of the changes to transmitters will also be reflected on our coverage checker at [digitaluk.co.uk/coveragechecker](http://digitaluk.co.uk/coveragechecker).

Note: Where multiplexes are moving we have included the current and future aerial group required to receive Freeview services. Digital UK recommends installers fitting new aerials use a wideband model where possible to accommodate future changes to broadcast frequencies.

#### Q3 2019

##### 14 August 2019

**Black Hill** – some relay stations only

##### 04 September 2019

**Darvel** – some relay stations only

##### 11 September 2019

**Black Hill** – Uplawmoor relay station only

##### 18 September 2019

**Angus** – main station only

## Previous Events

### Q3 2017

#### 26 July 2017

**Bressay** – some relay stations only

#### 23 August 2017

**Knockmore** – main and some relay stations

**Rumster Forest** – main and some relay stations

#### 6 September 2017

**Rosemarkie** – some relay stations only

#### 20 September 2017

**Eitshal** – some relay stations only

**Skriaig** – some relay stations only

### Q4 2017

#### 4 October 2017

**Torothy** – main and some relay stations

### Q3 2018

#### 15 August 2018

**Durris** – main station and some relay stations

#### 5 September 2018

**Black Hill** – main station and some relay stations

**Craigkelly** – some relay stations only

**Darvel** – main station and some relay stations

**Rosneath** – main station and some relay stations

#### 19 September 2018

**Black Hill** – some relay stations only

### Q4 2018

#### 3 October 2018

**Angus** – main station and Dundee Menzieshill relay

**Black Hill** – main station and Cumbernauld Village relay

**Craigkelly** – main station and some relay stations

**Durris** – main station only

**14 August 2019**

**The BLACK HILL transmitter group, serving Glasgow, central Scotland and parts of Edinburgh**

***Clachan***

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | A                   | Current  | 43          | 46          | 40          |
|                      |                     | 14.08.19 | 29          | 31          | 37          |

Power change: None

***Easdale***

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | A                   | Current  | 40          | 46          | 43          |
|                      |                     | 14.08.19 | 29          | 31          | 37          |

Power change: the ERP will change from 2W to 7W for all multiplexes

***Gigha Island***

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | A                   | Current  | 41+         | 44          | 47          |
|                      |                     | 14.08.19 | 29          | 31          | 37          |

Power change: None

***South Knapdale***

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | B                   | Current  | 60-         | 57          | 53          |
|                      |                     | 14.08.19 | 39          | 42          | 45          |

Power change: the ERP will change from 300W to 500W for all multiplexes

## South Knapdale HP

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| N/A                  | B                   | Current  | -           | -           | -           |
|                      |                     | 14.08.19 | 39          | 42          | 45          |

Power change: the ERP will launch at 20W for all multiplexes

## 4 September 2019

### The DARVEL transmitter group, serving parts of central Scotland, Argyll and Bute

#### Dunure

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | A                   | Current  | 46          | 43          | 40          |
|                      |                     | 04.09.19 | 32          | 34          | 35          |

Power change: None

#### Girvan - changes also occurred on 5 September 2018

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | A                   | Current  | 50          | 31          | 37          |
|                      |                     | 04.09.19 | 29          | 31          | 37          |

Power change: None

#### Troon

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | K                   | Current  | 49          | 58          | 54          |
|                      |                     | 04.09.19 | 29          | 37          | 48          |

Power change: None

## 11 September 2019

### The BLACK HILL transmitter group, serving Glasgow, central Scotland and parts of Edinburgh

#### Uplawmoor

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | A                   | Current  | 49          | 58          | 54          |
|                      |                     | 11.09.19 | 29          | 37          | 31          |

Power change: None

## 18 September 2019

### The ANGUS transmitter group, serving Angus, Dundee, Perth and parts of Fife

**Angus** - changes also occurred on 3 October 2018 & future changes to occur on 27 November 2019

| Current Aerial Group | Future Aerial Group |           | RF Channel  |             |             |            |             |             |
|----------------------|---------------------|-----------|-------------|-------------|-------------|------------|-------------|-------------|
|                      |                     |           | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) | COM4 (SDN) | COM5 (ARQA) | COM6 (ARQB) |
| CD                   | T                   | Current   | 60-         | 53          | 57          | 54         | 58          | 49          |
|                      |                     | 17.09.19* | 33          | 53          | 57          | 54         | 58          | 49          |

\*Transmissions commence on this date on the new frequency. Viewers will be required to retune on the following day, 18 September 2019.

|          | RF Channel  |             |      |
|----------|-------------|-------------|------|
|          | COM7 (NUK7) | COM8 (NUK8) | LOC1 |
| Current  | 55          | 56          | 48   |
| 17.09.19 | 55          | 56          | 48   |

Power change: None

26 July 2017

## The BRESSAY transmitter group, serving the Shetland Islands

### *Baltasound*

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | B                   | Current | 46-         | 43-         | 50          |
|                      |                     | Future  | 46-         | 43-         | 40          |

Power change: None

### *Scalloway*

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | A                   | Current | 50          | 59          | 55          |
|                      |                     | Future  | 32          | 34          | 35          |

Power change: None

### *Swinister*

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | A                   | Current | 50          | 59          | 55          |
|                      |                     | Future  | 32          | 34          | 35          |

Power change: None

### *Voe*

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | B                   | Current | 57          | 60          | 53          |
|                      |                     | Future  | 41          | 44          | 47          |

Power change: None

### Weisdale

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | Wideband            | Current | 58          | 49          | 54          |
|                      |                     | Future  | 33          | 36          | 48          |

Power change: None

## 23 August 2017

### The KNOCKMORE transmitter group, serving Morayshire, Strathspey and part of Easter Ross

#### Knockmore

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |            |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) | COM4 (SDN) | COM5 (ARQA) | COM6 (ARQB) |
| Wideband             | Wideband            | Current | 26          | 23          | 29          | 53         | 57          | 60-         |
|                      |                     | Future  | 31          | 37          | 29          | 33         | 36          | 48          |

Power change: None

#### Avoch

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | A                   | Current | 58          | 54          | 49          |
|                      |                     | Future  | 32          | 34          | 35          |

Power change: None

#### Balblair Wood

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | A                   | Current | 50          | 59          | 55          |
|                      |                     | Future  | 32          | 34          | 35          |

Power change: None

## **Craigellachie**

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | B                   | Current | 58          | 49          | 54          |
|                      |                     | Future  | 40          | 43          | 46          |

Power change: None

## **23 August 2017**

## **The RUMSTER FOREST transmitter group, serving Caithness and North Sutherland**

### **Rumster Forest**

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |            |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) | COM4 (SDN) | COM5 (ARQA) | COM6 (ARQB) |
| Wideband             | Wideband            | Current | 27          | 24          | 21+         | 30-        | 59          | 55          |
|                      |                     | Future  | 27          | 24          | 21+         | 32         | 34          | 35          |

Power change: None

### **Ben Tongue**

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | B                   | Current | 45          | 49          | 42          |
|                      |                     | Future  | 45          | 39          | 42          |

Power change: None

### **Durness**

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | B                   | Current | 57          | 53          | 60          |
|                      |                     | Future  | 41          | 44          | 47          |

Power change: None

### **Thurso**

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | B                   | Current | 57          | 60          | 53          |
|                      |                     | Future  | 41          | 44          | 47          |

Power change: None

## **6 September 2017**

### **The ROSEMARKIE transmitter group, serving Inverness and the Great Glen**

#### **Fodderty**

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | B                   | Current | 58          | 49          | 54          |
|                      |                     | Future  | 41          | 44          | 47          |

Power change: None

#### **Inverness**

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | A                   | Current | 50          | 55          | 59          |
|                      |                     | Future  | 29          | 31          | 37          |

Power change: None

## **20 September 2017**

### **The EITSHAL transmitter group, serving Lewis, Wester Ross, North West Sutherland and parts of Harris and Skye**

#### **Badachro**

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | B                   | Current | 46          | 43          | 50          |
|                      |                     | Future  | 46          | 43          | 40          |

Power change: None

**Kinlochbervie HP & VP**

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | B                   | Current | 46          | 43          | 50          |
|                      |                     | Future  | 46          | 43          | 40          |

Power change: None

**Lochinver**

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | B                   | Current | 46          | 43          | 50          |
|                      |                     | Future  | 46          | 43          | 40          |

Power change: None

**Staffin**

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | B                   | Current | 45          | 49          | 42          |
|                      |                     | Future  | 45          | 39          | 42          |

Power change: None

**Ullapool**

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | B                   | Current | 45          | 49          | 42          |
|                      |                     | Future  | 45          | 39          | 42          |

Power change: None

**20 September 2017**

**The SKRIAIG transmitter group, serving Skye, Harris, North Uist, Benbecula, South Uist and part of Barra**

***Daliburgh***

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | B                   | Current | 60          | 57          | 53          |
|                      |                     | Future  | 39          | 42          | 45          |

Power change: None

***Inverarish***

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | B                   | Current | 46          | 43          | 50          |
|                      |                     | Future  | 46          | 43          | 40          |

Power change: None

***Kilbride South Uist***

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | A                   | Current | 39          | 45          | 42          |
|                      |                     | Future  | 32          | 34          | 35          |

Power change: None

***Penifiler***

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | B                   | Current | 45          | 49          | 42          |
|                      |                     | Future  | 45          | 39          | 42          |

Power change: None

### **Scoval HP & VP**

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | B                   | Current | 50          | 59          | 55          |
|                      |                     | Future  | 40          | 43          | 46          |

Power change: None

### **Tarbert Harris**

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | A                   | Current | 45          | 39          | 42          |
|                      |                     | Future  | 32          | 34          | 35          |

Power change: None

## **4 October 2017**

### **The TOROSAY transmitter group, serving South West Highlands and Islands**

#### **Torosay**

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |            |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) | COM4 (SDN) | COM5 (ARQA) | COM6 (ARQB) |
| A                    | A                   | Current | 28          | 25          | 22          | 23         | 26          | 29          |
|                      |                     | Future  | 28          | 25          | 22          | 23         | 26          | 30          |

Power change: None

#### **Acharacle**

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | B                   | Current | 46          | 43          | 50          |
|                      |                     | Future  | 46          | 43          | 40          |

Power change: None

**Arisaig**

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| A                    | A                   | Current | 26          | 23          | 29          |
|                      |                     | Future  | 26          | 23          | 30          |

Power change: None

**Ballachulish**

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| A                    | A                   | Current | 23          | 29          | 26          |
|                      |                     | Future  | 23          | 30          | 26          |

Power change: None

**Bellanoch**

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | B                   | Current | 45          | 42          | 49          |
|                      |                     | Future  | 41          | 44          | 47          |

Power change: None

**Cow Hill**

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | B                   | Current | 46          | 43          | 50          |
|                      |                     | Future  | 46          | 43          | 40          |

Power change: None

**Fiunary**

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | B                   | Current | 46          | 43          | 50          |
|                      |                     | Future  | 46          | 43          | 40          |

Power change: None

### Glengorm

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | A                   | Current | 44+         | 41+         | 47+         |
|                      |                     | Future  | 29          | 31          | 37          |

Power change: None

### Kilmelford

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | A                   | Current | 50          | 59          | 55          |
|                      |                     | Future  | 29          | 31          | 37          |

Power change: None

### Kinlochleven

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | A                   | Current | 59          | 55          | 50          |
|                      |                     | Future  | 29          | 31          | 37          |

Power change: None

### Loch Feochan

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | A                   | Current | 54          | 49          | 58          |
|                      |                     | Future  | 32          | 34          | 35          |

Power change: None

### Mallaig

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | B                   | Current | 46-         | 43-         | 50          |
|                      |                     | Future  | 46-         | 43-         | 40          |

Power change: None

**Onich HP & VP**

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | A                   | Current | 49          | 54          | 58          |
|                      |                     | Future  | 32          | 34          | 35          |

Power change: None

**Strontain**

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | B                   | Current | 39          | 45          | 42          |
|                      |                     | Future  | 39          | 45          | 42          |

Power change: the ERP will change from 3W to 6W for all multiplexes

**Taynuilt**

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | B                   | Current | 46          | 43          | 50          |
|                      |                     | Future  | 46          | 43          | 40          |

Power change: None

**Tayvallich**

| Current Aerial Group | Future Aerial Group |         | RF Channel  |             |             |
|----------------------|---------------------|---------|-------------|-------------|-------------|
|                      |                     |         | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | B                   | Current | 46          | 43          | 50          |
|                      |                     | Future  | 46          | 43          | 40          |

Power change: None

**15 August 2018**

**The DURRIS transmitter group, serving Aberdeen and Aberdeenshire**

*Durris - further changes to occur on 3 October 2018*

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |            |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) | COM4 (SDN) | COM5 (ARQA) | COM6 (ARQB) |
| A                    | T                   | Current  | 28          | 25          | 22          | 23         | 26          | 29          |
|                      |                     | 15.08.18 | 28          | 25          | 22          | 23         | 26          | 29          |

|          | RF Channel  |             |      |
|----------|-------------|-------------|------|
|          | COM7 (NUK7) | COM8 (NUK8) | LOC1 |
| Current  | 32          | 35          | 30   |
| 15.08.18 | 55          | 56          | 41   |

Power change: None

**Balgownie**

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | B                   | Current  | 46          | 43          | 50          |
|                      |                     | 15.08.18 | 46          | 43          | 40          |

Power change: None

**Braemar**

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | B                   | Current  | 45          | 42          | 49          |
|                      |                     | 15.08.18 | 45          | 42          | 39          |

Power change: None

**Brechin**

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | B                   | Current  | 46          | 43          | 50          |
|                      |                     | 15.08.18 | 46          | 43          | 40          |

Power change: None

**Gartley Moor**

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | B                   | Current  | 58          | 49          | 54          |
|                      |                     | 15.08.18 | 41          | 44          | 47          |

Power change: None

**Gourdon**

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | A                   | Current  | 50          | 59          | 55          |
|                      |                     | 15.08.18 | 32          | 34          | 35          |

Power change: None

**Peterhead**

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | K                   | Current  | 50          | 59          | 55          |
|                      |                     | 15.08.18 | 33          | 36          | 48          |

Power change: None

**Tomintoul**

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | B                   | Current  | 46          | 43          | 50          |
|                      |                     | 15.08.18 | 46          | 43          | 40          |

Power change: None

## Tullich

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | A                   | Current  | 50          | 59          | 55          |
|                      |                     | 15.08.18 | 32          | 34          | 35          |

Power change: None

## 5 September 2018

### The BLACK HILL transmitter group, serving Glasgow, central Scotland and parts of Edinburgh

*Black Hill - further changes to occur on 3 October 2018*

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |            |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) | COM4 (SDN) | COM5 (ARQA) | COM6 (ARQB) |
| B                    | T                   | Current  | 46          | 43          | 40          | 41+        | 44          | 47          |
|                      |                     | 05.09.18 | 46          | 43          | 40          | 41+        | 44          | 47          |

|          | RF Channel  |             |      |
|----------|-------------|-------------|------|
|          | COM7 (NUK7) | COM8 (NUK8) | LOC1 |
| Current  | 32          | 35          | 51   |
| 05.09.18 | 55          | 56          | 51   |

Power change: None

### **Glasgow West Central**

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | A                   | Current  | 50          | 59          | 55          |
|                      |                     | 05.09.18 | 21          | 24          | 27          |

Power change: None

### **Kelvindale**

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | A                   | Current  | 52          | 56          | 48          |
|                      |                     | 05.09.18 | 29          | 31          | 37          |

Power change: None

### **Killearn**

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | A                   | Current  | 50          | 59          | 55          |
|                      |                     | 05.09.18 | 32          | 34          | 35          |

Power change: None

### **Kirkfieldbank**

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | A                   | Current  | 50          | 59          | 55          |
|                      |                     | 05.09.18 | 29          | 31          | 37          |

Power change: None

### **Netherton Braes**

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| A                    | A                   | Current  | 27          | 24          | 21+         |
|                      |                     | 05.09.18 | 23          | 26          | 29          |

Power change: the ERP will change from 2W to 4W for PSB3

## Rothesay Town

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | A                   | Current  | 50          | 59          | 55          |
|                      |                     | 05.09.18 | 29          | 31          | 37          |

Power change: None

## 5 September 2018

### The CRAIGKELLY transmitter group, serving Lothian, parts of Edinburgh and parts of Fife

*Aberfoyle - further changes to occur on 3 October 2018*

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | A                   | Current  | 55          | 50          | 59          |
|                      |                     | 05.09.18 | 32          | 50          | 59          |

Power change: the ERP will change from 18W to 33W for PSB1

*Cannongate HP & VP - further changes to occur on 3 October 2018*

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | A                   | Current  | 55          | 50          | 59          |
|                      |                     | 05.09.18 | 35          | 50          | 59          |

Power change: None

*Newbattle - further changes to occur on 3 October 2018*

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | B                   | Current  | 50          | 59          | 55          |
|                      |                     | 05.09.18 | 50          | 59          | 47          |

Power change: None

**5 September 2018**

**The DARVEL transmitter group, serving parts of central Scotland, Argyll and Bute**

***Darvel***

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |            |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) | COM4 (SDN) | COM5 (ARQA) | COM6 (ARQB) |
| A                    | T                   | Current  | 22-         | 25          | 28          | 23         | 26          | 29          |
|                      |                     | 05.09.18 | 22-         | 25          | 28          | 32         | 34          | 35          |

|          | RF Channel  |             |      |
|----------|-------------|-------------|------|
|          | COM7 (NUK7) | COM8 (NUK8) | LOC1 |
| Current  | 31          | 37          | 30   |
| 05.09.18 | 55          | 56          | 31   |

Power change: None

***Ayr South***

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | A                   | Current  | 45          | 39          | 42          |
|                      |                     | 05.09.18 | 26          | 29          | 37          |

Power change: the ERP will change from 2W to 4W for all multiplexes

***Bowmore HP & VP***

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | A                   | Current  | 47          | 41+         | 44          |
|                      |                     | 05.09.18 | 29          | 31          | 37          |

Power change: None

**Campbeltown** - further changes to occur in Q1 2020

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | B                   | Current  | 60          | 57          | 53          |
|                      |                     | 05.09.18 | 39          | 57          | 53          |

Power change: None

**Carradale**

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | B                   | Current  | 44          | 41+         | 47          |
|                      |                     | 05.09.18 | 44          | 41+         | 47          |

Power change: the ERP will change from 5W to 12W for all multiplexes

**Catrine**

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | B                   | Current  | 50          | 59          | 55          |
|                      |                     | 05.09.18 | 39          | 42          | 45          |

Power change: None

**Claonaig**

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | A                   | Current  | 50          | 59          | 55          |
|                      |                     | 05.09.18 | 29          | 31          | 37          |

Power change: the ERP will change from 15W to 30W for all multiplexes

**Girvan** - further changes to occur in Q3 2019

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | A                   | Current  | 50          | 59          | 55          |
|                      |                     | 05.09.18 | 50          | 31          | 37          |

Power change: None

### ***Kirkmichael***

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | B                   | Current  | 45          | 49          | 42          |
|                      |                     | 05.09.18 | 45          | 39          | 42          |

Power change: the ERP will change from 4W to 9W for all multiplexes

### ***Lethanhill***

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | K                   | Current  | 60          | 57          | 53          |
|                      |                     | 05.09.18 | 33          | 36          | 48          |

Power change: None

### ***Lochgoilhead***

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | B                   | Current  | 53          | 57          | 60          |
|                      |                     | 05.09.18 | 41          | 44          | 47          |

Power change: None

### ***Lochwinnoch***

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | K                   | Current  | 60          | 57          | 53          |
|                      |                     | 05.09.18 | 33          | 36          | 48          |

Power change: None

### ***Millburn Muir***

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | A                   | Current  | 42          | 45          | 39          |
|                      |                     | 05.09.18 | 29          | 31          | 37          |

Power change: None

## Portnahaven

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| A                    | A                   | Current  | 23          | 29          | 26          |
|                      |                     | 05.09.18 | 23          | 30          | 26          |

Power change: None

## 5 September 2018

### The ROSNEATH transmitter group, serving Rosneath

#### Rosneath HP & VP

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |            |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) | COM4 (SDN) | COM5 (ARQA) | COM6 (ARQB) |
| CD                   | K                   | Current  | 49          | 58          | 54          | 53         | 57          | 60-         |
|                      |                     | 05.09.18 | 39          | 42          | 45          | 33         | 36          | 48          |

Power change: None

#### Ardnadam

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | A                   | Current  | 42          | 45          | 39          |
|                      |                     | 05.09.18 | 29          | 31          | 37          |

Power change: None

#### Garelochhead

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | A                   | Current  | 42          | 45          | 39          |
|                      |                     | 05.09.18 | 29          | 31          | 37          |

Power change: None

## 19 September 2018

### The BLACK HILL transmitter group, serving Glasgow, central Scotland and parts of Edinburgh

#### Abington

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | B                   | Current  | 60          | 57          | 53          |
|                      |                     | 19.09.18 | 39          | 42          | 45          |

Power change: None

#### Bridge Of Allan

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| A                    | A                   | Current  | 26          | 23          | 29          |
|                      |                     | 19.09.18 | 26          | 23          | 30          |

Power change: None

#### Cathcart

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | B                   | Current  | 60          | 57          | 53          |
|                      |                     | 19.09.18 | 39          | 42          | 45          |

Power change: None

#### Deanston

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | B                   | Current  | 60          | 53          | 57          |
|                      |                     | 19.09.18 | 39          | 42          | 45          |

Power change: None

**Dollar**

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | A                   | Current  | 49          | 58          | 54          |
|                      |                     | 19.09.18 | 32          | 34          | 35          |

Power change: None

**Glespin**

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | A                   | Current  | 49          | 58          | 54          |
|                      |                     | 19.09.18 | 23          | 26          | 30          |

Power change: None

**Haddington**

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | K                   | Current  | 49          | 58          | 54          |
|                      |                     | 19.09.18 | 33          | 36          | 48          |

Power change: the ERP will change from 4W to 8W for all multiplexes

**Kirkconnel**

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | A                   | Current  | 49          | 58          | 54          |
|                      |                     | 19.09.18 | 29          | 31          | 37          |

Power change: None

**Largs**

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | A                   | Current  | 45          | 58          | 54          |
|                      |                     | 19.09.18 | 29          | 31          | 37          |

Power change: the ERP will change from 5W to 10W for all multiplexes

### Leadhills

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | A                   | Current  | 49          | 58          | 54          |
|                      |                     | 19.09.18 | 32          | 34          | 35          |

Power change: None

### Millport

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | A                   | Current  | 49          | 58          | 54          |
|                      |                     | 19.09.18 | 32          | 34          | 35          |

Power change: None

### New Cumnock

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | B                   | Current  | 43          | 46          | 50          |
|                      |                     | 19.09.18 | 43          | 46          | 40          |

Power change: None

### Tighnabruaich

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| B                    | B                   | Current  | 45          | 49          | 42          |
|                      |                     | 19.09.18 | 40          | 43          | 46          |

Power change: None

### Tillicoultry

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | B                   | Current  | 60          | 57          | 53          |
|                      |                     | 19.09.18 | 39          | 42          | 45          |

Power change: None

**3 October 2018**

**The ANGUS transmitter group, serving Angus, Dundee, Perth and parts of Fife**

*Angus - further changes to occur in Q3 2019 & Q4 2019*

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |            |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) | COM4 (SDN) | COM5 (ARQA) | COM6 (ARQB) |
| CD                   | T                   | Current  | 60-         | 53          | 57          | 54         | 58          | 49          |
|                      |                     | 03.10.18 | 60-         | 53          | 57          | 54         | 58          | 49          |

|          | RF Channel  |             |      |
|----------|-------------|-------------|------|
|          | COM7 (NUK7) | COM8 (NUK8) | LOC1 |
| Current  | 31          | 37          | 48   |
| 03.10.18 | 55          | 56          | 48   |

Power change: None

***Dundee Menzieshill***

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| A                    | A                   | Current  | 23          | 29          | 26          |
|                      |                     | 03.10.18 | 23          | 30          | 26          |

Power change: None

**3 October 2018**

**The BLACK HILL transmitter group, serving Glasgow, central Scotland and parts of Edinburgh**

*Black Hill - change also occurred on 05 September 2018*

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |            |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) | COM4 (SDN) | COM5 (ARQA) | COM6 (ARQB) |
| B                    | T                   | Current  | 46          | 43          | 40          | 41+        | 44          | 47          |
|                      |                     | 03.10.18 | 46          | 43          | 40          | 41+        | 44          | 47          |

|          | RF Channel  |             |      |
|----------|-------------|-------------|------|
|          | COM7 (NUK7) | COM8 (NUK8) | LOC1 |
| Current  | 55          | 56          | 51   |
| 03.10.18 | 55          | 56          | 30   |

Power change: the ERP will change from 5kW to 10kW for LOC1

**Cumbernauld Village**

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | K                   | Current  | 49          | 58          | 54          |
|                      |                     | 03.10.18 | 33          | 36          | 48          |

Power change: None

**3 October 2018**

**The CRAIGKELLY transmitter group, serving Lothian, parts of Edinburgh and parts of Fife**

***Craigkelly***

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |            |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) | COM4 (SDN) | COM5 (ARQA) | COM6 (ARQB) |
| K                    | T                   | Current  | 27          | 24          | 21+         | 42         | 45          | 39+         |
|                      |                     | 03.10.18 | 27          | 24          | 21+         | 29         | 31          | 37          |

|          | RF Channel  |             |      |
|----------|-------------|-------------|------|
|          | COM7 (NUK7) | COM8 (NUK8) | LOC1 |
| Current  | 33          | 34          | 30   |
| 03.10.18 | 55          | 56          | 32   |

Power change: None

***Aberfoyle*** - change also occurred on 05 September 2018

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | A                   | Current  | 32          | 50          | 59          |
|                      |                     | 03.10.18 | 32          | 34          | 35          |

Power change: the ERP will change from 18W to 33W for PSB2 and PSB3

***Cannogate HP & VP*** - change also occurred on 05 September 2018

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | A                   | Current  | 35          | 50          | 59          |
|                      |                     | 03.10.18 | 35          | 34          | 33          |

Power change: None

## Grangemouth

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | B                   | Current  | 53          | 60          | 57          |
|                      |                     | 03.10.18 | 39          | 42          | 45          |

Power change: None

## Kinross

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | A                   | Current  | 59          | 50          | 55          |
|                      |                     | 03.10.18 | 32          | 34          | 35          |

Power change: None

## Newbattle - change also occurred on 05 September 2018

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | B                   | Current  | 50          | 59          | 47          |
|                      |                     | 03.10.18 | 41          | 44          | 47          |

Power change: None

## Penicuik

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| CD                   | B                   | Current  | 54          | 49          | 58          |
|                      |                     | 03.10.18 | 39          | 42          | 45          |

Power change: None

## West Linton

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) |
| A                    | A                   | Current  | 29          | 23          | 26          |
|                      |                     | 03.10.18 | 30          | 23          | 26          |

Power change: None

**3 October 2018**

**The DURRIS transmitter group, serving Aberdeen and Aberdeenshire**

*Durris - change also occurred on 15 August 2018*

| Current Aerial Group | Future Aerial Group |          | RF Channel  |             |             |            |             |             |
|----------------------|---------------------|----------|-------------|-------------|-------------|------------|-------------|-------------|
|                      |                     |          | PSB1 (BBCA) | PSB2 (D3&4) | PSB3 (BBCB) | COM4 (SDN) | COM5 (ARQA) | COM6 (ARQB) |
| A                    | T                   | Current  | 28          | 25          | 22          | 23         | 26          | 29          |
|                      |                     | 03.10.18 | 28          | 25          | 22          | 23         | 26          | 30          |

|          | RF Channel  |             |      |
|----------|-------------|-------------|------|
|          | COM7 (NUK7) | COM8 (NUK8) | LOC1 |
| Current  | 55          | 56          | 41   |
| 03.10.18 | 55          | 56          | 41   |

Power change: None