

Issue: 16 July 2018

Update: 24 August 2018

- South Knapdale and Easdale clearance events removed from 19 September 2018

## Trade and Industry Information

### 700MHz Clearance Events

#### STV Region

Following a decision by Ofcom, spectrum in the 700MHz UHF band currently used for digital terrestrial television (DTT) is being reallocated for the development of future mobile services. Some DTT multiplexes will be moving to new broadcast frequencies as a result of this change.

Engineering work for the 700MHz Clearance Programme will take place at transmitters across the UK between 2017 - 2020. Freeview viewers (and those with other services that use Freeview channels, such as YouView) will need to retune their TV equipment when changes take place in their area. This document lists the currently announced clearance events for the STV region and will be updated as new information is released. The latest version will always be available to download at [www.digitaluk.co.uk/clearance](http://www.digitaluk.co.uk/clearance). Details of the changes to transmitters will also be reflected on our coverage checker at [digitaluk.co.uk/coveragechecker](http://digitaluk.co.uk/coveragechecker).

Note: Where multiplexes are moving we have included the current and future aerial group required to receive Freeview services. Digital UK recommends installers fitting new aerials use a wideband model where possible to accommodate future changes to broadcast frequencies.

#### Q3 2018

##### 15 August 2018

**Durris** – main station and some relay stations

##### 5 September 2018

**Black Hill** – main station and some relay stations

**Craigkelly** – some relay stations only

**Darvel** – main station and some relay stations

**Rosneath** – main station and some relay stations

##### 19 September 2018

**Black Hill** – some relay stations only

#### Q4 2018

##### 3 October 2018

**Angus** – main station and Dundee Menzieshill relay

**Black Hill** – main station and Cumbernauld Village relay

**Craigkelly** – main station and some relay stations

**Durris** – main station only

Changes denoted by  
light red background:

X

**15 August 2018**

**The DURRIS transmitter group, serving Aberdeen and Aberdeenshire**

*Durriss - further changes to occur on 3 October 2018*

Current Aerial Group	Future Aerial Group		RF Channel					
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)	COM4 (SDN)	COM5 (ARQA)	COM6 (ARQB)
A	T	Current	28	25	22	23	26	29
		15.08.18	28	25	22	23	26	29

	RF Channel		
	COM7 (NUK7)	COM8 (NUK8)	LOC1
Current	32	35	30
15.08.18	55	56	41

Power change: None

**Balgownie**

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	46	43	50
		15.08.18	46	43	40

Power change: None

**Braemar**

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	45	42	49
		15.08.18	45	42	39

Power change: None

### **Brechin**

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	46	43	50
		15.08.18	46	43	40

Power change: None

### **Gartley Moor**

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	58	49	54
		15.08.18	41	44	47

Power change: None

### **Gourdon**

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	50	59	55
		15.08.18	32	34	35

Power change: None

### **Peterhead**

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	K	Current	50	59	55
		15.08.18	33	36	48

Power change: None

### **Tomintoul**

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	46	43	50
		15.08.18	46	43	40

Power change: None

## Tullich

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	50	59	55
		15.08.18	32	34	35

Power change: None

## 5 September 2018

### The BLACK HILL transmitter group, serving Glasgow, central Scotland and parts of Edinburgh

*Black Hill* - further changes to occur on 3 October 2018

Current Aerial Group	Future Aerial Group		RF Channel					
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)	COM4 (SDN)	COM5 (ARQA)	COM6 (ARQB)
B	T	Current	46	43	40	41+	44	47
		05.09.18	46	43	40	41+	44	47

	RF Channel		
	COM7 (NUK7)	COM8 (NUK8)	LOC1
Current	32	35	51
05.09.18	55	56	51

Power change: None

### **Glasgow West Central**

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	50	59	55
		05.09.18	21	24	27

Power change: None

### **Kelvindale**

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	52	56	48
		05.09.18	29	31	37

Power change: None

### **Killearn**

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	50	59	55
		05.09.18	32	34	35

Power change: None

### **Kirkfieldbank**

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	50	59	55
		05.09.18	29	31	37

Power change: None

### **Netherton Braes**

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
A	A	Current	27	24	21+
		05.09.18	23	26	29

Power change: the ERP will change from 2W to 4W for PSB3

## Rothesay Town

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	50	59	55
		05.09.18	29	31	37

Power change: None

## 5 September 2018

### The CRAIGKELLY transmitter group, serving Lothian, parts of Edinburgh and parts of Fife

*Aberfoyle - further changes to occur on 3 October 2018*

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	55	50	59
		05.09.18	32	50	59

Power change: the ERP will change from 18W to 33W for PSB1

*Cannongate HP & VP - further changes to occur on 3 October 2018*

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	55	50	59
		05.09.18	35	50	59

Power change: None

*Newbattle - further changes to occur on 3 October 2018*

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	50	59	55
		05.09.18	50	59	47

Power change: None

## 5 September 2018

### The DARVEL transmitter group, serving parts of central Scotland, Argyll and Bute

#### Darvel

Current Aerial Group	Future Aerial Group		RF Channel					
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)	COM4 (SDN)	COM5 (ARQA)	COM6 (ARQB)
A	T	Current	22-	25	28	23	26	29
		05.09.18	22-	25	28	32	34	35

	RF Channel		
	COM7 (NUK7)	COM8 (NUK8)	LOC1
Current	31	37	30
05.09.18	55	56	31

Power change: None

#### Ayr South

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	A	Current	45	39	42
		05.09.18	26	29	37

Power change: the ERP will change from 2W to 4W for all multiplexes

#### Bowmore HP & VP

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	A	Current	47	41+	44
		05.09.18	29	31	37

Power change: None

**Campbeltown** - further changes to occur in Q1 2020

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	60	57	53
		05.09.18	39	57	53

Power change: None

**Carradale**

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	44	41+	47
		05.09.18	44	41+	47

Power change: the ERP will change from 5W to 12W for all multiplexes

**Catrine**

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	50	59	55
		05.09.18	39	42	45

Power change: None

**Claonaig**

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	50	59	55
		05.09.18	29	31	37

Power change: the ERP will change from 15W to 30W for all multiplexes

**Girvan** - further changes to occur in Q3 2019

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	50	59	55
		05.09.18	50	31	37

Power change: None



### ***Kirkmichael***

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	45	49	42
		05.09.18	45	39	42

Power change: the ERP will change from 4W to 9W for all multiplexes

### ***Lethanhill***

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	K	Current	60	57	53
		05.09.18	33	36	48

Power change: None

### ***Lochgoilhead***

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	53	57	60
		05.09.18	41	44	47

Power change: None

### ***Lochwinnoch***

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	K	Current	60	57	53
		05.09.18	33	36	48

Power change: None

### ***Millburn Muir***

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	A	Current	42	45	39
		05.09.18	29	31	37

Power change: None

## Portnahaven

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
A	A	Current	23	29	26
		05.09.18	23	30	26

Power change: None

## 5 September 2018

### The ROSNEATH transmitter group, serving Rosneath

#### Rosneath HP & VP

Current Aerial Group	Future Aerial Group		RF Channel					
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)	COM4 (SDN)	COM5 (ARQA)	COM6 (ARQB)
CD	K	Current	49	58	54	53	57	60-
		05.09.18	39	42	45	33	36	48

Power change: None

#### Ardnadam

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	A	Current	42	45	39
		05.09.18	29	31	37

Power change: None

#### Garelochhead

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	A	Current	42	45	39
		05.09.18	29	31	37

Power change: None

## 19 September 2018

### The BLACK HILL transmitter group, serving Glasgow, central Scotland and parts of Edinburgh

#### Abington

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	60	57	53
		19.09.18	39	42	45

Power change: None

#### Bridge Of Allan

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
A	A	Current	26	23	29
		19.09.18	26	23	30

Power change: None

#### Cathcart

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	60	57	53
		19.09.18	39	42	45

Power change: None

#### Deanston

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	60	53	57
		19.09.18	39	42	45

Power change: None

**Dollar**

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	49	58	54
		19.09.18	32	34	35

Power change: None

**Glespin**

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	49	58	54
		19.09.18	23	26	30

Power change: None

**Haddington**

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	K	Current	49	58	54
		19.09.18	33	36	48

Power change: the ERP will change from 4W to 8W for all multiplexes

**Kirkconnel**

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	49	58	54
		19.09.18	29	31	37

Power change: None

**Largs**

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	A	Current	45	58	54
		19.09.18	29	31	37

Power change: the ERP will change from 5W to 10W for all multiplexes

### Leadhills

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	49	58	54
		19.09.18	32	34	35

Power change: None

### Millport

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	49	58	54
		19.09.18	32	34	35

Power change: None

### New Cumnock

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	43	46	50
		19.09.18	43	46	40

Power change: None

### Tighnabruaich

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
B	B	Current	45	49	42
		19.09.18	40	43	46

Power change: None

### Tillicoultry

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	60	57	53
		19.09.18	39	42	45

Power change: None

**3 October 2018**

**The ANGUS transmitter group, serving Angus, Dundee, Perth and parts of Fife**

*Angus - further changes to occur in Q3 2019 & Q4 2019*

Current Aerial Group	Future Aerial Group		RF Channel					
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)	COM4 (SDN)	COM5 (ARQA)	COM6 (ARQB)
CD	T	Current	60-	53	57	54	58	49
		03.10.18	60-	53	57	54	58	49

	RF Channel		
	COM7 (NUK7)	COM8 (NUK8)	LOC1
Current	31	37	48
03.10.18	55	56	48

Power change: None

***Dundee Menzieshill***

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
A	A	Current	23	29	26
		03.10.18	23	30	26

Power change: None

**3 October 2018**

**The BLACK HILL transmitter group, serving Glasgow, central Scotland and parts of Edinburgh**

*Black Hill - change also occurred on 05 September 2018*

Current Aerial Group	Future Aerial Group		RF Channel					
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)	COM4 (SDN)	COM5 (ARQA)	COM6 (ARQB)
B	T	Current	46	43	40	41+	44	47
		03.10.18	46	43	40	41+	44	47

	RF Channel		
	COM7 (NUK7)	COM8 (NUK8)	LOC1
Current	55	56	51
03.10.18	55	56	30

Power change: the ERP will change from 5kW to 10kW for LOC1

**Cumbernauld Village**

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	K	Current	49	58	54
		03.10.18	33	36	48

Power change: None

**3 October 2018**

**The CRAIGKELLY transmitter group, serving Lothian, parts of Edinburgh and parts of Fife**

***Craigkelly***

Current Aerial Group	Future Aerial Group		RF Channel					
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)	COM4 (SDN)	COM5 (ARQA)	COM6 (ARQB)
K	T	Current	27	24	21+	42	45	39+
		03.10.18	27	24	21+	29	31	37

	RF Channel		
	COM7 (NUK7)	COM8 (NUK8)	LOC1
Current	33	34	30
03.10.18	55	56	32

Power change: None

***Aberfoyle*** - change also occurred on 05 September 2018

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	32	50	59
		03.10.18	32	34	35

Power change: the ERP will change from 18W to 33W for PSB2 and PSB3

***Cannogate HP & VP*** - change also occurred on 05 September 2018

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	35	50	59
		03.10.18	35	34	33

Power change: None



## Grangemouth

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	53	60	57
		03.10.18	39	42	45

Power change: None

## Kinross

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	A	Current	59	50	55
		03.10.18	32	34	35

Power change: None

## Newbattle - change also occurred on 05 September 2018

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	50	59	47
		03.10.18	41	44	47

Power change: None

## Penicuik

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
CD	B	Current	54	49	58
		03.10.18	39	42	45

Power change: None

## West Linton

Current Aerial Group	Future Aerial Group		RF Channel		
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)
A	A	Current	29	23	26
		03.10.18	30	23	26

Power change: None

### 3 October 2018

## The DURRIS transmitter group, serving Aberdeen and Aberdeenshire

*Durris - change also occurred on 15 August 2018*

Current Aerial Group	Future Aerial Group		RF Channel					
			PSB1 (BBCA)	PSB2 (D3&4)	PSB3 (BBCB)	COM4 (SDN)	COM5 (ARQA)	COM6 (ARQB)
A	T	Current	28	25	22	23	26	29
		03.10.18	28	25	22	23	26	30

	RF Channel		
	COM7 (NUK7)	COM8 (NUK8)	LOC1
Current	55	56	41
03.10.18	55	56	41

Power change: None